TAURUS Y TAURUS Y-100K

Type	TAURUS Y-100K
Input voltage variation	%
Rated power	100 kVA
Input voltage range	240V-440V V
Max input current	152 A
Output voltage	380 V
Rated output current	A
Efficiency	98 %
Adjustment speed	1 ÷ 3 ms/V
Dimensions WxDxH	570x780x1270mm
Weight	246 kg

Standard features

Voltage stabilisation	Independent phase control
Selectable output voltage	380V - 200V
Frequency	49Hz ÷ 62Hz
Output voltage accuracy	±2 ÷ ±3%
Cooling	Natural ventilation up to 15kVA, aided with fans from 20kVA
Ambient temperature	-5/+40°C
Admitted overload	50%
Harmonic distortion	None introduced
Colour	RAL 9005
Protection degree	IP 2X
Instrumentation	Input & Output digital multimetre
Installation	Indoor
Protections	Input circuit breaker Manual by-pass

Optional Standard Accessories

R 2 | 8 | 2022